

Enova DVX All-In-One Presentation Switchers

PRODUCT COMPARISON CHART

Presentation Switcher	Model	NX Series Control	Amplifier	Multi-Format Inputs	HDMI Inputs	DXLink Inputs	Analog Audio Inputs	Scaled HDMI Outputs	DXLink Twisted Pair Outputs	Analog Audio Outputs	Control Ports (Serial/IR/IO/Relay)
4x2	DVX-2210HD-SP	YES	2x25w - 8 Ohm	2	2	0	4	2	1**	3	4/4/4/4
	DVX-2210HD-T	YES	75w -70V/100V	2	2	0	4	2	1**	3	4/4/4/4
6x3	DVX-2250HD-SP	YES	2x25w - 8 Ohm	2	4	0	4	2	1*	3	4/4/4/4
	DVX-2250HD-T	YES	75w -70V/100V	2	4	0	4	2	1*	3	4/4/4/4
	DVX-2255HD-SP	YES	2x25w - 8 Ohm	2	2	2	4	2	1*	3	4/4/4/4
	DVX-2255HD-T	YES	75w -70V/100V	2	2	2	4	2	1*	3	4/4/4/4
10x4	DVX-3250HD-SP	YES	2x25w - 8 Ohm	4	6	0	8	4	2**	4	8/8/8/8
	DVX-3250HD-T	YES	75w -70V/100V	4	6	0	8	4	2**	4	8/8/8/8
	DVX-3255HD-SP	YES	2x25w - 8 Ohm	4	4	2	8	4	2**	4	8/8/8/8
	DVX-3255HD-T	YES	75w -70V/100V	4	4	2	8	4	2**	4	8/8/8/8
	DVX-3256HD-SP	YES	2x25w - 8 Ohm	2	4	4	6	4	2**	4	8/8/8/8
	DVX-3256HD-T	YES	75w -70V/100V	2	4	4	6	4	2**	4	8/8/8/8

* DVX-225x DXLink output is an independent, unscaled output with power. Scaling occurs at DXLink Receiver.

** DVX-2210 and DVX-325x DXLink outputs are unpowered, paired with an HDMI output & contain identical audio & video content & resolution as companion HDMI output.