ClearOne.

Beamforming Microphone Array 2



ClearOne's second-generation Beamforming Mic Array is the professional-grade microphone array with beamforming and adaptive steering, ClearOne's next-generation Acoustic Echo Cancellation and Noise Cancellation.

The ultra-sleek design fits into any conferencing environment and delivers the clearest audio pickup available with its Acoustic Intelligence.

2nd Generation Mic Array

- + Beamforming & adaptive steering technology
- + Most advanced AEC & NC
- + Acoustic Intelligence with adaptive ambience
- + Replaces 9 to 12 traditional microphones

Ultra Sleek Design

- + Three mounting options Ceiling, Wall & Table
- + Two power options: P-link, PoE
- + Standard ceiling projector mount

Flexible & Scalable

- + Daisy-chain up to 3 arrays per CONVERGE® Pro 2 unit
- + Zero-consumption of CONVERGE Pro 2 analog inputs
- + Single cable for power, audio & control
- + Daisy-chain with DIALOG[®] 20 Wireless Mic System

Configuration & Management

- + New CONVERGE Pro 2 CONSOLE software
- + Auto-discovery of devices
- + System monitoring and troubleshooting



Telemedicine Facilities

VENUES

Boardrooms

Conference Rooms

Large Lecture Halls

Training Centers

Courtrooms


Houses of Worship




Rear Connections




Connection Diagrams





Operating Modes







Table





Wall







Functional Specifications

24 microphones 1 Channel In (does not take up any input channels in CONVERGE Pro 2) Number of Beams 5 in Ceiling mode 6 in Table mode 5 in Wall mode Polar Pattern: Custom Frequency Response: 150Hz - 16kHz, +/- 3dB Dynamic Range: 150Hz – 16kHz, >70dB

LED & TOUCH SENSOR

Sensor Type: 2 Capacitive Touch Button for Mute LED (2x: one on each end of a unit):

- Power On
- » Power On & Unmuted: Blue
- » Muted: Red
- Power Off: No light

BEAMFORMING MIC ARRAY 2 CONFIGURATION

Beam enable/disable		
Mounting mode selection:		
Auto		
Ceiling		
Wall		
Table		
Acoustic Echo Cancellation (AEC) on/off		
Noise Cancellation (NC) on/off		
Filters:		
All Pass		
Low Pass		
High Pass		
Notch		
PEQ		
Automatic Level Control (ALC) on/off		
Gain adjust		
Mute on/off		
Auto gate/Manual gate		

USB

For future use

P-LINK PERIPHERAL BUS

P-Link In & Out: Proprietary Peripheral Bus Ports Type: RJ-45 Cable

Solid core 24AWG, factory terminated Cat 5e or Cat 6 Distance: Up to 200 feet Daisy Chain:

- Up to 3 Beamforming Microphone Array 2 units with each supported CONVERGE Pro 2 unit in the same chain
- Up to 3 Beamforming Microphone Array 2 units and up to 3 DIALOG 20 Wireless Receiver units with each supported CONVERGE Pro 2 unit in the same chain
- Up to 6 Beamforming Microphone Array 2 units in the same chain with 2 supported CONVERGE Pro 2 units connected through C-Link

SALES AND INQUIRIES

Tel: +1 801.975.7200 TollFree: +1 800.945.7730 TechSales: +1 800.705.2103 Fax: +1 801.303.5711 sales@clearone.com

POWER SELECTION SWITCH

Sensor Type: Slide Switch

- · Toggle toward P-Link to power device by P-Link
- Toggle toward PoE to power device by PoE Injector or PoE Ethernet Switch

CONFIGURATION & ADMINISTRATION SOFTWARE

CONVERGE Pro 2 CONSOLE Software

COMMANDS

Through supported CONVERGE Pro 2 unit connected through P-Link

MOUNTING

Ceiling mount kit (12", 24", 36", and 48" suspension column) Wall mount kit Table mount

POWER & THERMAL

Power Type: PoE Port Type: RJ-45 Power Source: P-Link or PoE Injector PoF In: PoF IEEE 802 3at Power Source Indicator: Set the position of the power source to indicate the source of the power (P-Link or PoE) Mains Voltage: 100-240VAC, 50/60Hz AC Power Consumption: 12W Typical DC Power Consumption: 5.26W Typical Thermal: 40.95 BTU/Hr Operating Temperature: 14° F/-10° C to 104° F/40° C ambient temperature

DIMENSION & WEIGHT (WxHxD)

30" x 1" x 5.75" (762mm x 25.4mm x 146mm) Unit Weight: 4.4 lbs (2.0kg) Shipping Weight: 5.7 lbs (2.59kg)

PART NUMBERS

910-3200-201: White Beamforming Microphone Array 2 910-3200-201-B: Black Beamforming Microphone Array 2

SUPPORTED CONVERGE PRO 2

Part Number	Product	
910-3200-001	CONVERGE Pro 2 128	
910-3200-001-D	CONVERGE Pro 2 128D	
910-3200-002	CONVERGE Pro 2 128T	
910-3200-002-D	CONVERGE Pro 2 128TD	
910-3200-003	CONVERGE Pro 2 128V	
910-3200-003-D	CONVERGE Pro 2 128VD	
910-3200-005	CONVERGE Pro 2 48T	
910-3200-004	CONVERGE Pro 2 120	

-----٨

ACCESSORIES		
Part Number	Product	
910-3200-202	PoE Power supply kit for BFM	
910-3200-203-12	BFM2 Ceiling Mount kit with 12" Suspension Column - White	
910-3200-203-12-B	BFM2 Ceiling Mount kit with 12" Suspension Column - Black	
910-3200-203-24	BFM2 Ceiling Mount kit with 24" Suspension Column - White	
910-3200-203-24-B	BFM2 Ceiling Mount kit with 24" Suspension Column - Black	
910-3200-203-36	BFM2 Ceiling Mount kit with 36" Suspension Column - White	
910-3200-203-36-B	BFM2 Ceiling Mount kit with 36" Suspension Column -Black	
910-3200-203-48	BFM2 Ceiling Mount kit with 48" Suspension Column - White	
910-3200-203-48-B	BFM2 Ceiling Mount kit with 48" Suspension Column - Black	
910-3200-203	BFM2 Ceiling Mount kit without Suspension column - White	
910-3200-203-B	BFM2 Ceiling Mount kit without Suspension column - Black	
910-001-005-12	BFM White Ceiling Mount kit with 12" suspension column	
910-001-005-12-B	BFM Black Ceiling Mount kit with 12" suspension column	
910-001-005-24	BFM White Ceiling Mount kit with 24" suspension column	
910-001-005-24-B	BFM Black Ceiling Mount kit with 24" suspension column	
910-001-005-36	BFM White Ceiling Mount kit with 36" suspension column	
910-001-005-48	BFM White Ceiling Mount kit with 48" suspension column	
910-001-006	BFM White Wall Mount kit	
910-001-006-B	BFM Black Wall Mount kit	
910-3200-204-50	50 Ft RJ45 CAT6 Cable	
910-3200-204-100	100 Ft RJ45 CAT6 Cable	
910-3200-204-150	150 Ft RJ45 CAT6 Cable	
910-3200-204-200	200 Ft RJ45 CAT6 Cable	

Middle East Tel: +1.800.945.7730 Tel: +1.800.945.7730 Tel: +1.800.945.7730

global@clearone.com global@clearone.com global@clearone.com

Tel: +1.800.945.7730 global@clearone.com

Other product names may be registered trademarks of their respective owners who do not necessarily endorse ClearOne or ClearOne's products. All rights reserved. Information in this document subject to change without notice. © 2016 ClearOne.