



HDMI 4x4 True Matrix Switcher Splitter v1.3b with RS232

The CSW-HD440 HDMI matrix switcher routes high definition video in multiple resolutions up to 4Kx2K@30Hz plus multichannel digital audio from any of the four HDMI sources to the displays. Four outputs give you the choices of sending high definition audio and video signals up to four displays. Any four to any four matrix switching allows for maximum versatility for integrated systems. The CSW-HD440 eliminates the need to disconnect and reconnect sources to a display equipped with one input. It works with Blu-ray DVD players, TiVo systems, HT PCs, and satellite set top boxes that connect to an HDMI display. Every source is accessible at all times by any display by selecting it with front panel push buttons, an IR remote or through the RS-232 port. Always use Comprehensive brand premium cables to ensure maximum performance!



Features

- Allows any HDMI display to view any source at any time
- Allows any source to be displayed on multiple displays at the same time
- Maintains resolutions up to 4Kx2K@30Hz
- Maintains highest HDMI single link video resolution
- Maintains highest HDMI digital audio signal
- HDMI or DVI to HDMI cables are used to connect the inputs and the matrix output
- Each display's inputs can be switched with the IR remote control or through RS232
- Supports HDCP
- Supports HDMI 1.4

Specifications

Video Amplifier Bandwidth: 2.97Gbps

Input Video Signal: 1.2 volts p-p, 4 HDMI female connectors

Output Video Signal: 1.2 volts p-p, 4 HDMI female connectors

Input DDC Signal: 5 volts p-p (TTL)

Video Resolutions: 480i to 4Kx2K@30Hz

Remote Control Port: RS-232 female, 3.5mm Mini-Stereo

Power Supply: 12V DC

Power Consumption: 20 watts (max)

Rackmountable: Yes

Weight: 2.5lbs

Warranty: 2 Years

CSW-HD440 - HDMI 4x4 True Matrix Switcher Splitter v1.3b with RS232