



RC-2

Wall Plate – RS-232 Controller



The RC-2 is a 2-button controller that sends a series of RS-232 commands with the push of a button. It operates serial devices such as projectors, displays & switchers.

FEATURES

- 2 Back Lit & Label Capable Buttons.
- 1 RS-232 Port - Controls a device via serial control protocols.
- Optional Ports - Add control ports with the PL-18 Control Port Expander.
- Memory - Each button can be programmed with up to four macro sequences.
- Dimensions - 7.9cm x 1.59cm x 12.4cm (3.12" x 0.63" x 4.88") US; 8.6cm x 1.59cm x 8.6cm (3.39" x 0.63" x 3.39") and 8cm x 1.59cm x 8cm (3.15" x 0.63" x 3.15") EU W, D, H.
- Wall Plate Size - 1 gang EU/US.



RC-2

TECHNICAL SPECIFICATIONS

PORTS: 1 RS-232 on a terminal block connector.

POWER SOURCE: 12V DC, 40mA.

DIMENSIONS: 7.9cm x 1.59cm x 12.4cm (3.12" x 0.63" x 4.88") US; 8.6cm x 1.59cm x 8.6cm (3.39" x 0.63" x 3.39") and 8cm x 1.59cm x 8cm (3.15" x 0.63" x 3.15") EU W, D, H.

WEIGHT: 0.3kg (0.67lbs) approx.

ACCESSORIES: Power supply.

OPTIONS: RK-121WP 19" rack adapter, RS-232 9-pin D-sub port to 3-pin terminal block connector cable.