



KRAMER

VA-1VGAN

Computer Graphics Video EDID Emulator

| VGA/UXGA - 15-pin HD



The VA-1VGAN is an EDID emulator for computer graphics video signals. The unit can capture an EDID setting in non-volatile memory from the output allowing convenient and reliable connection to the source

FEATURES

Bandwidth - 1.8GHz

Control - Capture button



KRAMER

TECHNICAL SPECIFICATIONS

INPUT:	1 XGA input on a 15pin HD (F) connector
OUTPUT:	1 XGA output on a 15pin HD (F) connector
MAX. OUTPUT LEVEL:	>2Vpp
BANDWIDTH (-3dB):	1.8GHz
DIFF. GAIN:	0.02%
DIFF. PHASE:	0.02Deg
K-FACTOR:	<0.05%
S/N RATIO:	74dB @5MHz (unweighted: 66dB)
CONTROLS:	Button for EDID capture
COUPLING:	DC, direct wiring between input and output
PRODUCT DIMENSION:	6.22cm x 5.18cm x 2.44cm (2.45" x 2.04" x 0.96") W, D, H
PRODUCT WEIGHT:	0.1kg (0.2lbs) approx
SHIPPING DIMENSION:	15.70cm x 12.00cm x 8.70cm (6.18" x 4.72" x 3.43") W, D, H
SHIPPING WEIGHT:	0.4kg (0.9lbs) approx
POWER CONSUMPTION:	5V DC, 20mA
INCLUDED ACCESSORIES:	Power supply
OPTIONS:	RK4PT 19" rack adapter

